

DC Surge Diverter, 50 kA – TDS502BR300DC





- Designed to provide economical and reliable protection from transients on DC power systems
- Compact design fits into inverters and solar combiner boxes
- Conveniently packaged for easy installation on DIN rail
- Separate plug and base design allows hot swappable module replacement







Part Number	TDS502BR300DC
Nominal System Voltage (Un)	300 VDC
Max Continuous Operating Voltage (Uc)	350 VDC
Voltage Protection Rating (VPR)	1,800.0 V @ 3 kA - to PE 1,800.0 V @ 3 kA + to PE
Nominal Discharge Current (In)	20 kA 8/20 μs
Max Discharge Current (Imax)	50 kA 8/20 μs
Frequency	0 – 100 Hz
Protection Modes	-ve to PE +ve to PE
Technology	Gas Discharge Tube (GDT) Metal Oxide Varistor (MOV)
Connection, Solid	35 mm² Max
Connection, Stranded	25 mm² Max
Mounting	35 mm top hat DIN rail
Enclosure Material	UL® 94V-0 Thermoplastic
Enclosure Rating	IP 20 NEMA®-1
Remote Contacts	Yes
Status Indication	Mechanical flag
Temperature	-40 to 80 ℃
Module Width	2 M
Depth (D)	68 mm
Height (H)	90 mm
Width (W)	35 mm
Unit Weight	0.24 kg





Part Number	TDS502BR300DC
Certification Details	UL [*] 1449 Edition 3 for PV Applications
Complies With	ANSI®/IEEE® C62.41.2-2002 Cat A, Cat B, Cat C ANSI®/IEEE® C62.41.2-2002 Scenario II, Exposure 2, 50 kA 8/20 μs
Replacement Module	TDS150M277
Certifications	cURus
Standard Packaging Quantity	1 рс
UPC	78285666495
EAN-13	8711893066326

ANSI is a registered trademark of American National Standards Institute. IEEE is a registered trademark of The Institute of Electrical and Electronics Engineers, Inc. NEMA is a registered service mark of National Electrical Manufacturers Association. UL, UR, cUL, cUR, cULus and cURus are registered certification marks of UL LLC.

WARNING

Pentair products shall be installed and used only as indicated in Pentair's product instruction sheets and training materials. Instruction sheets are available at erico.pentair.com and from your Pentair customer service representative. Improper installation, misuse, misapplication or other failure to completely follow Pentair's instructions and warnings may cause product malfunction, property damage, serious bodily injury and death and/or void your warranty.

© 2017 Pentair All rights reserved
Pentair, CADDY, CADWELD, CRITEC, ERICO, ERIFLEX, ERITECH and LENTON are owned by Pentair or its global affiliates.
All other trademarks are the property of their respective owners. Pentair reserves the right to change specifications without prior notice.

